




INSTRUCTIONS

1. Connect battery (12V only) to the terminal identified with a "+" tag.
2. Ground the terminal with a "-" tag.
3. Your switch panel is supplied with 6 fuses -6x5A.
First decide what rating of fuse should be used for each switch.
(WARNING: DO not use fuse rated over 15A).
4. To remove the fuseholder cap, see diagram below.



"PUSH ↓" indicates slot
in the fuseholder body.

Insert a ball pen or small
screw driver in the slot.
Press downward.

Cap pops out. Insert or
remove fuse, then snap
cap back to position.

Fuse bar is positive (+)
Switch bar is negative (-)
Center tap on switch goes to positive (+) on appliance
*Make sure negative (-) of appliance is connected (-) on same ground
The negative wire (-) or Ground wire (-) on the appliance must be
connected to a common negative Ground (-) on the instrument panel.
Example-negative terminal ammeter.

